

- It has got a screen on inspector so you can easily see the end surface
- Corresponding to USB 2.0 connector and enable to save the end surface picture in the computer



Confirmation



Cleaning



Confirmation of cleaning

The cleaner is equipped so enable to clean the end surface

- It is used dry battery (it works approximately 4 hours)



View Conn VC-6100 仕様

Monitor	3.5 inch TFT-LCD
Size	170mm x 95mm x 30.5mm
View size	~400μm x 300μm
Focus	Manual adjustment, maximum amplification 2mm
Magnification	16.8 power (3.5 inch), 40.0 power (more than 9 inch, only in PC case)
Battery	It works 4 hours approximately (continuous running)
USB	USB For 1.1 or 2.0, For Windows2000/XP
ATT	Plug phenol attachment (For φ1.25 and φ2.5) For PC software (CD-ROM)
Option	Spare of cleaner AC adapter For APC phenol attachment

For PC (USB2.0) surface inspector probe CI-1000-B



surface inspector probe CI-1000-B

Size	φ32mm x 175mm
View size	~400μm x 300μm
Focus	Manual adjustment maximum movable scope = 2mm
Magnification	40.0 power (more than 9 inch, only in PC case)
USB	USB For 1.1 or 2.0 For Windows2000/XP
ATT	Jack attachment (For both SC, FC and LC) Plug phenol attachment (For φ1.25, φ2.5 and φ2.5APC) For PC software (CD-ROM)

